

# ADVANTAGE - 2000+

## Installation Instructions :

- # 2226-CNT : 26" wide Cantilevered Shelf - Solid Surface 18" deep.
- # 2250-CNT : 50" wide Cantilevered Shelf - Solid Surface 18" deep.
- # 2272-CNT : 72" wide Cantilevered Shelf - Solid Surface 18" deep.
- # 2226-CNT-SLT : 26" wide Cantilevered Shelf - Slotted Surface 18" deep.
- # 2250-CNT-SLT : 50" wide Cantilevered Shelf - Slotted Surface 18" deep.
- # 2272-CNT-SLT : 72" wide Cantilevered Shelf - Slotted Surface 18" deep.
- # 2226-CNT-LT : 26" wide Light Duty Cantilevered Shelf - Solid Surface 18" deep.
- # 2250-CNT-LT : 50" wide Light Duty Cantilevered Shelf - Solid Surface 18" deep.
- # 2272-CNT-LT : 72" wide Light Duty Cantilevered Shelf - Solid Surface 18" deep.

## Mounting shelf to uprights :

**STEP (1):** Lay the shelf down with the bottom facing up. Mount the cantilevered shelf brackets to the shelf into the threaded holes marked 'M' with the screws provided (#12-24x1/2" lg.). The Light Duty shelf has only four mounting holes and will not be marked. Use the straight edge of the shelf bracket to mount to the solid shelf surfaces with the smooth edge of the brackets facing the outside of the shelf and the mounting ears opposite the leading radius edge of the shelf surface.(fig.1)

The slotted shelf surfaces can also be mounted level or at 15 degrees tilt towards the user, by reversing the brackets, using the angled edge of the brackets.(fig.2)

**STEP (2):** Choose the desired height location of the shelf and start (2) screws 3" apart vertically in the rear set of upright mounting holes when a level shelf is desired; or 2" apart vertically when an angled slotted shelf is being mounted. On the opposing upright's mounting holes (the holes that face each other on the uprights where you wish to span the shelf either 26", 50", or 72" apart) start (2) screws in the same height location. Leave approx. 3/16" threads exposed(ref. diagram).

Lift the cantilevered shelf bracket assembly onto the set of screws (the mounting bracket slot should slide onto the top screw). The shelf and bracket assembly will slide onto the screws and then fall into place. Secure the shelf surface by placing screws into the (3) remaining mounting bracket screw hole locations and tighten!

